

Surface Mount Schottky Rectifier Reverse Voltage 20V to 60V Forward Current 3A

DO-214AC (SMA)

Features

- Schottky barrier diodes
- Low forward voltage drop
- High Tunction Temperature
- Moisture sensitivity: level 1, per J-STD-020
- Plastic package has Underwriters Laboratory Flammability Classification 94V-0
- Add suffix "E" for Halogen Free
- Halogen-free according to IEC 61249-2-21 definition
- AEC-Q101 qualified

Typical Applications

For use in low voltage, high freqency inverters, free wheeling, and polarity protection application

Maximum Ratings (TA = 25 °C unless otherwise noted)							
Parameter	Symbol	SK32A SK32AE	SK33A SK33AE	SK34A SK34AE	SK35A SK35AE	SK36A SK36AE	Unit
Maximum repetitive peak reverse voltage	V _{RRM}	20	30	40	50	60	V
Maximum RMS voltage	V _{RMS}	14	21	28	35	42	V
Maximum DC blocking voltage	V _{DC}	20	30	40	50	60	V
Maximum average forward rectified current	I _{F(AV)}	3.0			А		
Peak forward surge current 8.3 ms single half sine-wave superimposed on rated load	I _{FSM}	100			А		
Operating junction and storage temperature range	T_J, T_STG	- 55 to + 150			°C		

Electrical Characteristics (TA = 25 °C unless otherwise noted)								
Parameter	Test Conditions	Symbol	SK32A SK32AE	SK33A SK33AE		SK35A SK35AE	SK36A SK36AE	Unit
Maximum instantaneous forward voltage	I _F =3A, T _A =25℃	V_{F}	0.50 0.70		70	V		
Maximum DC reverse current	T _A =25℃	I _R		0.20		0.15		mA
at rated DC blocking voltage	T _A =125℃	^{'R} 10			ША			
Typical junction capacitance	4.0 V, 1 MHz	CJ	250				pF	

Thermal Characteristics							
Parameter	Symbol	SK32A SK32AE	SK33A SK33AE		SK35A SK35AE		Unit
	$R_{ extsf{ heta}JA}$		-	77	-		
Typical thermal resistance ⁽¹⁾	R _{θJC}	40					°C/W
	R _{θJI}	18					

Note1:Thermal resistance from junction to lead,mounted on PCB with 5.0×5.0mm copper pads



Surface Mount Schottky Rectifier Reverse Voltage 20V to 60V Forward Current 3A

Ratings and Characteristics Curves



Figure 1. Forward Current Derating Curve



Figure 2.Maximum Non-Repetitive Peak Forward Surge Current





Surface Mount Schottky Rectifier

Reverse Voltage 20V to 60V Forward Current 3A



ure 6. Typical Reverse Characteristic (SK35A thru SK36A)



Surface Mount Schottky Rectifier Reverse Voltage 20V to 60V Forward Current 3A

Package Outline Dimensions

in inches (millimeters)



MOUNTING PAD LAYOUT



Packing Information

7500 pcs/Reel, 18 Reels/Box; 12mm Tape, 13" Reel

Tape & Reel Specification





Symbo	SMA (mm)
W	12 ± 0.2
Е	1.75 ± 0.1
F	5.5 \pm 0.05
DO	1.5 ± 0.1
D1	1.50 +0.1/-0
PO	4.0 ± 0.1
P1	4.0 ± 0.1
P2	2.0 ± 0.05
AO	2.65 \pm 0.1
B0	5.25 \pm 0.1



Surface Mount Schottky Rectifier Reverse Voltage 20V to 60V Forward Current 3A

Soldering Parameters



Reflow Soldering		Sn-Pb Eutectic Assembly	Pb-Free assembly	
	- Temperature Min (Ts(min))	100 °C	150 °C	
Pre Heat	- Temperature Max (Ts(max))	150 °C	$200\mathrm{C}$	
	- Time (min to max) (ts)	60 – 120 secs	60 – 180 secs	
Average ramp up rate (Liquidu	is) Temp (TL) to peak	3 °C/second max	3 °C/second max	
TS(max) to TL - Ramp-up Rate		3 °C/second max	3 °C/second max	
Reflow	- Temperature (TL) (Liquidus)	183 °C	217 °C	
Kellow	- Time (min to max) (ts)		60 – 150 seconds	
Peak Temperature (TP)		240+0/-5 °C	240+0/-5 °C	
Time within 5 °C of actual peal	x Temperature (tp)	10–30 seconds	20-40 seconds	
Ramp-down Rate		6 °C/second max	6 °C/second max	
Time 25 $^{\circ}$ C to peak Temperature (TP)		6 minutes Max.	8 minutes Max.	
Do not exceed		260 °C	260 °C	

Wave Soldering	
Peak Temperature :	260+0/-5 ℃
Dipping Time :	10 seconds
Soldering :	1 time



Surface Mount Schottky Rectifier Reverse Voltage 20V to 60V Forward Current 3A

Disclaimers

These materials are intended as a reference to assist our customers in the selection of the Suzhou Good-Ark product best suited to the customer's application; they do not convey any license under any intellectual property rights, or any other rights, belonging to Suzhou Good-Ark Electronics Co., Ltd.or a third party.

Suzhou Good-Ark Electronics Co., Ltd. assumes no responsibility for any damage, or infringement of any third-party's rights, originating in the use of any product data, diagrams, charts, programs, algorithms, or circuit application examples contained in these materials.

All information contained in these materials, including product data, diagrams, charts, programs and algorithms represents information on products at the time of publication of these materials, and are subject to change by Suzhou Good-Ark Electronics Co., Ltd. without notice due to product improvements or other reasons. It is therefore recommended that customers contact Suzhou Good-Ark Electronics Co., Ltd. or an authorized Suzhou Good-Ark Electronics Co., Ltd. for the latest product information before purchasing a product listed herein. The information described here may contain technical inaccuracies or typographical errors. Suzhou Good-Ark Electronics Co., Ltd. assumes no responsibility for any damage, liability, or other loss rising from these inaccuracies or errors. Please also pay attention to information published by Suzhou Good-Ark Electronics Co., Ltd. by various means, including our website home page. (http://www.goodark.com)

When using any or all of the information contained in these materials, including product data, diagrams, charts, programs, and algorithms, Please be sure to evaluate all information as a total system before making a final decision on the applicability of the information and products. Suzhou Good-Ark Electronics Co., Ltd. assumes no responsibility for any damage, liability or other loss resulting from the information contained herein.

The prior written approval of Suzhou Good-Ark Electronics Co., Ltd. is necessary to reprint or reproduce in whole or in part these materials.

Please contact Suzhou Good-Ark Electronics Co., Ltd. or an authorized distributor for further details on these materials or the products contained herein.